

MFT-X1

Multifunction tester



- True Loop™ test with patented Confidence Meter™
- CertSuite™ compatible Bluetooth® result transfer
- Next generation 2-wire and 3-wire non-trip loop testing
- User upgradeable operating system
- High resolution 0.001Ω loop test
- Automatic volt-drop measurement
- Stabilised insulation test voltage
- Configurable RCD and EV auto-sequence tests
- Fast switch rechargeable plug-in battery pack
- Full colour TFT bonded display
- Re-designed lead set and carry case solution
- IP54 operational housing

DESCRIPTION

The MFT-X1 new electrical installation testing platform MFT-X1 is the first of a new generation of firmware upgradeable, full functionality multi-function testers for low voltage electrical installations.

Intended for use on all low voltage electrical installations including EV charge points and domestic photo-voltaic systems, the range of test capabilities allow for general commissioning of installations and periodic maintenance as well as detailed fault diagnostics.

FEATURES

True Loop™

True Loop™ impedance testing is now a standard feature on the MFT-X1. The latest 3-wire non-trip loop testing technology, incorporated with the patented Confidence Meter™, offers an unmatched, reliable, accurate, stable and repeatable loop test solution to the user, allowing testing in the most hostile high noise conditions or close to the source of supply. The technology also removes the risk of RCD uplift whilst reducing typical test times – even on circuits protected 10 mA protective devices.

Patented Confidence meter technology

All loop impedance ranges are now supported by the Megger patented Confidence meter technology, reducing typical test times for non-trip loop testing to around 7 seconds on quiet circuits, and providing optimised test times for loop impedance testing in difficult noisy supplies. The Confidence meter shows the progress of the loop measurement and indicates the presence of noise on the circuit, removing erroneous values to give a stable and consistent result.

MFT-X1 result downloading and CertSuite

Test results can be tagged with circuit data and transferred to CertSuite, the latest cloud base electrical certification software package from Megger.

When paired to a mobile device using the low energy Bluetooth® mode, results can be sent directly from the MFT-X1 to an Android or IOS device running Megger CertSuite software. These results are also synchronised with the cloud-based application.

With a wide range of certification options, CertSuite is available as a monthly or yearly subscription package for electrical certification of installations taking results directly from the MFT whilst testing. CertSuite is suitable for multiple concurrent users and is optimised for use with the MFT-X1.

Results can be stored and reviewed remotely by users whilst on site from different locations, accessed by head office or other users with the relevant permission, with professional looking certification and reports.

MFT-X1

Multifunction tester

High resolution loop impedance testing

The MFT-X1 has extended the low end of the loop impedance range from 0.01 ohms to 0.001 ohms resolution and 50 kA current calculation. The True Loop impedance measurement using the patented confidence meter makes these low impedance measurements a realistic option, with two wire test connections and high current testing.

RCD custom testing

RCD testing can now be optimised with the RCD test configurator. Select a whole suite of tests or only those elements of the RCD you require. You can even add ramp testing to the sequence, optimising and simplifying testing.

EV Charge point testing

Suitable for both EV charger installation testing with either RCD Type B or RDC protected charge points. The MFT-X1 in conjunction with the Megger EVCA adaptor can test all known EV chargers for installation or maintenance.

Stabilised insulation test voltage

For the first time in any multifunction tester, the MFT-X1 incorporates a stabilised insulation test voltage, ensuring output voltage is accurate to within +/-3% +2 digits. This compares to the industry standard of +20% and so provides a more accurate test voltage without the risk of over-voltage damage to circuits or sensitive components.

Current measurement

The MFT-X1 uses current clamps for current measurement using the optional Megger MCC1010* current clamp for measurement of AC currents from 1 mA to 1000 A.

*Optional accessory

Customer upgradeable operating system

The operating system of the MFT-X1 range is upgradeable by the user, simply by downloading the latest operating system file (.BIN) from the Megger web site to a suitable microSD card.

Insert the updated microSD card and pressing TEST initiates an automatic update process without the need for further user intervention.

Display and user interface

The user interface utilises the flexibility of the high contrast 480 x 272 colour, TFT bonded display, with a monochrome black on white mode designed specifically for use in difficult lighting conditions.

Enhancing the colour coded test selection rotary dial, range selection is now replicated on the instrument screen, ensuring easy use in poor lighting environments. Hot keys for second level functions are clearly shown across the top of each screen and the second control dial provides users with a further quick selection option of any highlighted feature, even if wearing protective gloves.

Relevant information is clearly shown on the display, both before and after each test, in full colour, and includes the Confidence Meter™ progress bar, RCD ramp test progress as well as the insulation and continuity measurement bar graph. The new Voltage Widget, displays the L-N, L-E and N-E voltages.

Li-ION Battery solution

The Megger MFT-X1 is powered by the Megger Li-ION battery pack. The unique 4 Ahr rechargeable Li-ION battery provides the fastest and most flexible battery change solution in the industry.

APPLICATIONS

The primary application is the testing of low voltage electrical installations in domestic, commercial, and industrial installations for single and three phase systems.

The wide range of test capabilities extend the use of the MFT-X1 to include:

- EV charge point testing
- Domestic PV testing
- Motor/Generator testing
- Machine testing
- Portable appliance safety testing
- Panel building and switchgear manufacturing
- Cable testing

Graphical assistance

The instrument has context help to provide graphical circuit connection guidance for each of the measurements.

Accessories

The MFT-X1 is shipped in a rugged, weather-proof carry case offering outstanding protection and flexible storage. Also included is a complete set of test leads to meet the wide range of connection challenges in modern electrical systems.

MFT-X1

Multifunction tester

FUNCTIONAL SUMMARY

Voltage measurement	
Voltage range	0.001 V to 2 V (mV range) 2 V to 600 V (V range), 1000 V DC (on-CAT rated circuits)
Voltage type:	Trms, AC, DC
Phase sequence	Automatic phase sequence testing on detection of valid three phase supplies
Current measurement (non-contact)	
AC Trms	Using optional accessories: MCC1010 current clamp
Measurement Range	MCC1010: 1 mA to 300 A
Continuity/Resistance	
Measurement range Digital display	0.01 Ω to 999 k Ω Auto-ranging
Measurement Range Analogue arc	0 Ω to 1 M Ω log scale
Test voltage	4 V DC to 5 V DC
Test current (Nominal)	>200 mA 0 Ω >< 2 Ω 10 mA Auto reduction on high resistance (actual current reported in display)
Test polarities	Forward polarity
Buzzer resistance range	> 0.01 Ω < 2 k Ω
Buzzer threshold	0.3, 0.5, 1, 2, 3, 4, 5, 10, 20, 30, 40, 50, 100, 200 Ω
Insulation testing	
Measurement range Digital display	0.001 M Ω to 999 M Ω Auto-ranging
Measurement range Analogue arc	0.001 M Ω to >1000 M Ω log scale
Insulation test voltages	50 V DC to 1000 V DC + Variable 50 V to 999 V
Test current	1 mA to 2 mA
Stabilised output voltage	Output test voltage stabilised to -0% +2% +2 V
True Loop™ loop impedance testing	
2 Wire – all modes	
Test types	Mode 1: Non-Trip Mode 2: High current Mode 3: High resolution
Resolution	Non-Trip: 0.01 Ω High current: 0.01 Ω High resolution: 0.001 Ω
Voltage range	Non-trip: 48 V AC to 280 V AC High current: 48 V AC to 550V AC High resolution: 48 V AC to 550 V AC
Frequency range	45 Hz to 65 Hz (all modes)

MFT-X1

Multifunction tester

3 Phase testing	Non-trip: Single phase only High current: Three phase High resolution: Three phase
3 wire - non-trip	
Test types	RCD (non-trip) RCD EV (non-trip on 6mA EV RDCs)
Resolution	0.01 Ω
Voltage range	48 V AC to 280 V
Frequency range	45 Hz to 65 Hz
3 Phase testing	Single phase only
Volt drop	
Volt drop calculation	Requires Zref (Ze) and circuit current (I-vdrop)
Accuracy	Dependent on loop impedance accuracy
RCD testing	
RCD types supported	Type AC, A, B, AC(S), A(S), B(S)
Auto RCD sequence	1/2x I Δ n, 1x I Δ n, 2x I Δ n, 5x I Δ n, Ramp, 0°/180° (customer configurable)
Ramp testing	10 mA to 1000 mA
RDC testing	6 mA RDC
Fault (Touch) voltage	0 V to 253 V
Earth testing	
2 wire	2 wire earth resistance test



MFT-X1

Multifunction tester

SPECIFICATIONS

Voltage measurement

Function	Range	Accuracy
Voltage DC	0 V ... ±1000 V	±1% ± 3 digits
Voltage AC/TRMS	0 V – 600 V (15 – 500 Hz)	±2% ± 1 digits
Frequency	15 Hz – 99 Hz	±0.5% ± 2 digit
	100 Hz – 500 Hz	±2.0% ± 2 digit

Millivolt measurement

Function	Range	Accuracy
mV AC/TRMS	0 mV to ±1999 mV (50 / 60 Hz)	±1% ± 3 digits
mV DC	0 mV to ±1999 mV	±1% ± 3 digits

Live Earth detection

Indicates if the PE terminal is live when selecting the Loop or RCD test ranges. The relevant Loop or RCD test is inhibited.

Current

Function	Range	Accuracy
Current AC/TRMS	0.001 A – 0.100 A	±2% ±3 digits
	0.100 A – 2.000 A	±2% ±3 digits
	2.00 A – 20.00 A	±2% ±3 digits
	20.0 A – 300.0 A	±2% ±3 digits
Frequency Bandwidth	15 Hz – 500 Hz	
Influence of Frequency	30 Hz – 500 Hz ≤0.25 %	

Resistance and Continuity

Function	Range	Test Current	Accuracy
200 mA	0.01 Ω – 99.9 Ω	(0 Ω – 2 Ω) 205 mA ±5 mA	±3% ±2 digits
10 mA	0.01 Ω – 99.9 Ω	10 mA	±3% ±2 digits
	100 Ω – 999 kΩ		±5% ±2 digits
Open circuit voltage	4 V to 5 V		

EN61557-4 Measurement Range: 0.10 Ω to 999 kΩ.

MFT-X1

Multifunction tester

Insulation test

Function	Range	Accuracy
1000 V	0.001 – 999 MΩ	±3% ±2 digits
500 V	0.001 – 500 MΩ	±3% ±2 digits
	> 500 MΩ	±10%
250 V	0.001 – 250 MΩ	±3% ±2 digits
	> 250 MΩ	±10%
100 V	0.001 – 100 MΩ	±3% ±2 digits
	> 100 MΩ	±10%
50 V	0.001 – 50 MΩ	±3% ±2 digits
	> 50 MΩ	±10%
VAR	Leakage current > 1 mA	±3% ±2 digits
50 V – 999 V	Leakage current < 1 mA	±10%
Leakage current	0.1 μA – 1.99 mA	±10%
Output voltage	-0% +2% +2 V at rated load or less	
Voltage display	±1% ± 3 V	
Short circuit current	1.5 mA nominal	
Test current on load	1 mA at min pass values of insulation	
Maximum capacitance	2 μF for a stable reading, 5 μF absolute limit	

EN61557-2 Measurement Range: 0.10 MΩ to 999 MΩ.

Loop 2-Wire - No RCD (L-PE, L-N or L-L)

Function	Range	Accuracy
2-Wire HR	0.001 – 9.999	±2% ±0.030 Ω
2-Wire	0.01 Ω - 9.99 Ω	±2% ±5 digits
	10.0 Ω - 99.9 Ω	±10% ±5 digits
	100 Ω - 1999 Ω	±10% ±5 digits
Supply Voltage	48 V – 550 V	
Supply Frequency	45 Hz – 65 Hz	

Can be used to measure supply source resistance quickly and reliably between Line and PE or two Live conductors up to 550 V.

EN61557-3 Measurement Range: 0.30 Ω to 1999 Ω

Loop 2-Wire L-PE with RCD

Function	Range	Accuracy
	0.01 Ω - 1999 Ω	±10% ±5 digits
Supply Voltage	48 V – 280 V	
Supply Frequency	45 Hz – 65 Hz	

Note: Uses the Megger Confidence Meter to measure the supply source impedance of circuits protected with an RCD rated ≥ 30 mA when there are only two connections possible. When a neutral is available the three-wire test will provide a quicker, more accurate result.

Note: RCD may trip if there are high leakage currents in the circuit under test. This measurement is immune to the effect of inductance found in some RCDs as it measures resistance (RCD Uplift).

EN61557-3 Measurement Range: 1.00 Ω to 1999 Ω

MFT-X1

Multifunction tester

Loop 3-Wire L-PE with RCD

Designation	Test Current	Application
RCD	15 mA	For circuits protected by an RCD rated ≤ 30 mA
RDC EV	3 mA	For EV charger circuits protected by a RDC and a Type A RCD rated ≤ 30 mA

Function	Range	Accuracy
	0.01 Ω - 9.99 Ω	$\pm 2\%$ ± 5 digits
	10.0 Ω - 199.9 Ω	$\pm 10\%$ ± 5 digits
Supply Voltage	48 V – 280 V	
Supply Frequency	45 Hz – 65 Hz	

Note: Uses the Megger Confidence Meter to measure the supply source impedance of circuits protected with an RCD when three connections are possible. The L-N Loop resistance needs to be less than 12 Ω . The resistances of the L-PE, L-N and N-PE loops are all shown, and the accuracy of the L-PE resistance depends on the maximum resistance displayed. When the neutral is not available the two-wire test must be used.

Note: RCD may trip if there are high leakage currents in the circuit under test. This measurement is immune to the effect of inductance found in some RCDs as it measures resistance.

EN61557-3 Measurement Range: 1.00 Ω to 1999 Ω

RCD Tests

Types A and AC

RCD Types	AC, A, AC(S), A(S)
RCD Rated Current ($I_{\Delta n}$)	10 mA, 30 mA, 100 mA, 300 mA, 500 mA, 650 mA, 1000 mA, VAR
$\frac{1}{2}$ I no-trip Test Current	-10% – +0% 0.5 $I_{\Delta n}$
1 I, 2 I, 5 I trip test – AC current	-0% – +10% $M \cdot I_{\Delta n}$
1 I, 2 I, 5 I trip test – pulsed DC current	-0% – +10% 1.4 • $M \cdot I_{\Delta n}$
Trip time	$\pm 10\%$
Ramp trip test current	$\pm 5\%$
Fault Voltage (0 V – supply)	+5% +15% ± 0.5 V
Supply Voltage	48 V – 280 V
Supply Frequency	45 Hz – 65 Hz

Type B

RCD Types	B, B(S)
RCD Rated Current ($I_{\Delta n}$)	10 mA, 30 mA, 100 mA, 300 mA
$\frac{1}{2}$ I no-trip Test Current	-10% – +0% (0.5 $I_{\Delta n}$)
1 I, 2 I, 5 I trip test Current	-0% – +10% (2 $I_{\Delta n}$)
Trip time	$\pm 10\%$
Trip current (ramp)	$\pm 5\%$
Fault Voltage (0 V – supply)	+5% +15% ± 0.5 V
Supply Voltage	48 V – 280 V
Supply Frequency	45 Hz – 65 Hz

MFT-X1

Multifunction tester

RDC (Type EV) with a 30 mA Type A RCD

Test current	2.0 mA increasing to 6.3 mA over 2s, before being held at that current for 10s.
Trip time	±1% ±1 ms
Trip current (ramp)	± 5%
Fault Voltage (0 V – supply)	+5% +15% ±0.5 V
Supply Voltage	48 V – 280 V
Supply Frequency	45 Hz – 65 Hz

Earth

Function	Range	Accuracy
2-Wire test	0.01 Ω – 1999 Ω	±2% ±3 digits
Test Frequency		128 Hz
Test Current		4.5 mA
Maximum auxiliary electrode resistance		5 kΩ

Note: The 2-wire earth test measures resistance between the blue and green terminals using a 128 Hz square wave; the result includes the resistance of test leads.

EN61557-5 Measurement Range: 1 Ω to 1999 Ω.

Power supply

Li-ION rechargeable	7.2 V DC 4400 mAh* (non-serviceable) + charge status indication
Battery charger (Li-ion)	Input: 110 V/ 230 V AC 50/60Hz 1.3 A Output: 3 A 8.4 V DC
Battery Life	Li-ion: 4400 mAh = >15 hrs* *times based on typical daily test profile
Battery Charging Time	Li-ion: 2.5 to 3 hrs (ambient temperature dependent)

Environmental

Conditions	Range
Operating Temperature	-10 °C to +55 °C
Storage Temperature	-25 °C to +70 °C
Operating Humidity	90% R.H. at +40 °C max
Ingress Protection	IEC 60529: IP 54 : Equipment is protected against ingress of dust and water splashes and is suitable for indoor and outdoor use.
Vibration	MIL-PRF-28800F:class 2
Max. operating altitude	2000 m
Pollution degree	2

Mechanical

Length	274 mm (10.79 ")
Width	96 mm (3.78 ")
Depth	143 mm (5.63 ")
Weight – Instrument only	1.57 kg (3.46 lb)
Shipping weight	5.6 kg (12.35 lb)

MFT-X1

Multifunction tester



ORDERING INFORMATION

Description	Part number	Description	Part number
MFT-X1-BS Multifunction tester BS1363	1012-223		
MFT-X1-SC Multifunction tester Schuko	1012-225		
MFT-X1-CH Multifunction tester Switzerland	1012-229		
MFT-X1-AU Multifunction tester AUS/NZ	1012-230		
Included accessories			
Switched test probe SP5			
Red test lead, probes, clips and grabbers			
Blue test lead, probe, clips and grabbers			
Green test lead, probe, clips and grabbers			
Earth test spike and leads kit			
Li-ion battery 4400 mAh			
Li-ion battery charger			
SIA10 MAINS socket interface adaptor UK (boxed)			
Neck strap			
Multipurpose hard base carry case			
Quick start guide			
Calibration certificate			
Optional and replacement accessories			
Multipurpose hard base carry case		1014-985	
Blow moulded carry case (Polypropylene)		1013-453	
Switched test probe SP5		1002-774	
Neck strap replacement		1013-454	
Li-ion battery 4400 mAh		1013-450	
SIA10 MAINS socket interface adaptor UK (boxed)		1014-300	
SIA20 Mains socket interface adaptor AU		1007-170	
SIA40 Mains socket interface adaptor SCHUKO		1007-171	
SIA45 Bipolar Mains socket interface adaptor SCHUKO		1007-158	
SIA50 Mains socket interface adaptor CH		1007-164	
SIA60 Mains socket interface adaptor USA		1007-087	
Li-ion battery charger		1013-451	
3 lead set RD/GN/BU non-fused (boxed)		1014-291	
3 lead pro set RD/GN/BU non-fused (boxed)		1014-292	
3 lead set RD/GN/BU fused 10 A (boxed)		1014-295	
3 piece grabber set RD/GN/BU (boxed)		1014-299	
7 piece probe and clip set RD/GN/BU (boxed)		1014-301	
3 lead RD/GN/BU fused 10 A (boxed) – fused leads only		1014-304	
Earth test spike and leads kit		1001-810	
MCC1010 Current clamp		1010-516	
MVC1010 Voltage clamp		1010-518	
MSA1363 socket adaptor UK		1013-837	
MTF230 – Schuko (Type-F) Socket adaptor		1013-838	
LA-KIT Lamp adaptor kit		1014-833	
UKAS Calibration certificate		1013-460	