## **AVOLVD15**

## Non-Contact Voltage Detector





■ Voltage detection: 50V~1000V AC

■ Frequency: 50~500 Hz

Measurement category : CAT. 600V

Indication : LED and Tone

Operating Conditions Temperature : 0~40°C

Humidity: Less than 80% R.H. Altitude: 2000m (6500 feet) maximum

For indoor use only.

■ Pollution degree : 2

■ Dimension : 142(L) x 28(W) x 27(D) mm

■ Weight: 45g (batteries included)

Power supply : 1.5V AAA battery x 2

The LVD-15 non-contact Voltage Detector is intended to check for the presence of AC voltage, signaling the user with an intermittent tone and a flashing LED. The non-contact Voltage Detector is used to detect voltage in outlets, lighting fixtures, circuit breakers, wires, and cables or to find a break in a wire.

Bright LED and audible alarm sound when voltage is present.

Designed for non-contact voltage detection. It's safer.

Can be used to find a break in a wire.

Flash light function.

ON/OFF switch for longer battery life.





